



# Another Industry First From Conlux!

Conlux is introducing new coin changers in China.

With its fine harmony of cutting-edge technology and user-friendly designing,  
we will dedicate to the growth of future-promising market.

## EXCLUSIVE FEATURES

- **Front Tube Cassette** : Self recognition by coin changer means no programming needed by service technician, thus no possibility of errors being made in programming.
- **Easy Loading Tube Cassette** : Tubes can be pre-loaded two ways: (1) through the top of the tube or (2) by opening the tube and placing a roll of coins in at one time.
- **Smart Payout** : Makes sure coin was paid out and if not, will try to pay that coin out one more time, resulting in less service calls.
- **Anti-Salting System** : Our uniquely designed diversion channel will protect your changer and vendor from salt water damage and vandalism.
- **Swing Open Payout Base** : No tools needed to remove base for cleaning or to discard foreign material.
- **Last Coin Payout** : No dead inventory.

**CONLUX**®

NIPPON CONLUX CO.,LTD.

# CONLUX CCX5G SERIES

## ADDITIONAL FEATURES

- Removable Coin Cassette •Coin Payout •LED Diagnostics
- Coin Capacity Control (Float) •SERIAL Interface
- No manual programming needed •Simple design-fewer parts

## SPECIFICATIONS

•Interface	SERIAL
•Operating Voltage	24Volt D.C 8Volt D.C
•Power Consumption	Stand by 0.09A
•Operating State	Motor Operation 0.88A. Peak Max. 5sec. 1.10A
•Operating Temperature Range	-15°C to +60°C
•Insulation Resistance	20M Ohm or more
•Weight	1.9Kg. (4.2Lbs.)
•Dimensions	(HxWxD) 376mmx137mmx82mm
•Number of Motors	1 Motor-15Volt D.C.
•Number of Solenoids	3 for Coin Selection (15 Volt D.C.)
•Chinese Coin Acceptance	5 JIAO, 1 YUAN
•Maximum Coin Capacity ( ± 3Coins Each Tube)	A Tube 1 YUAN 70 COINS B Tube 5 JIAO 79 COINS E Tube 5 JIAO 87 COINS

## DIAGNOSTICS and CONTROL FUNCTIONS

1.Two LED's are provided to indicate coin changer or discriminator malfunctions. LED(DIS) Red indicates discriminator malfunction and LED(C/C) indicates coin changer malfunctions. In operating state, both LED's are ON. Corresponding LED's will blink if a failure is detected, in either coin changer or discriminator section.

2.Use switches A thru E, to inventory coins from the corresponding tubes. The functions "SAT," "MOD," and "AUT" switches are explained in detail in the service manual.

DIS=discriminator  
C/C=coin changer

